

Model 6239 Audio and Video XLR 3-Pin & BNC Coax Interface, A/B Switch, Manual, Desktop

- **Switches Audio & NTSC Composite Video channels to either of two locations.**

INTRODUCTION

The Model 6239 allows quick and easy connection of Audio and Video channels to either of two remote locations. The audio channel utilizes XLR 3-pin microphone connectors and cabling. The video channel utilizes BNC Coax connectors and cabling. The Model 6239 is controlled via a front panel rotary switch. All three pins of the XLR connectors, and both center conductor & shell of the BNC connectors are switched simultaneously.

FEATURES:

- Allows quick and easy connection of local audio and video channels to either of two remote locations.
- High quality sealed switch with self-wiping low impedance contacts.
- Manual operation via front-panel rotary switch.
- All three pins of the XLR audio connector are switched.
- Both the shield and center conductor of the BNC connector are switched.
- Simultaneously switches both the audio and video channels.
- Eliminates the need to plug and unplug cables.
- No external power required.
- Attractive anodized black box packaging provides EMI/RFI shielding.
- Custom length cables available for your switch installation.
- Lifetime guarantee against manufacturing defects.



Specifications:

PORT CONNECTORS:

(3) XLR 3-pin female connectors labeled A, B, and COMMON.

(3) BNC female connectors labeled A, B, and COMMON.

FRONT PANEL CONTROLS: (1) Rotary switch on front panel selects A or B.

POWER: No power required. Manually operated.

DIMENSIONS: 8.0" W x 3.0" H x 8.0" D.
(20.3 x 7.6 x 20.3 cm)

WEIGHT: Approximately 1.5 lbs. (0.7 Kg)

Model 6239 Application

