



Electro Standards Laboratories
ADVANCED SYSTEMS DESIGN & SERVICES

SPECIFICATIONS
MODEL 9050
(Cat. No. 309050)

LineSelect® Model 9050 16-Channel RJ11/12 A/B Switch, Manual Rackmount

- Ideal for fax, modem and phone line switch applications.
- Eliminates need for dedicated phone lines for fax or modem.

INTRODUCTION:

With each of its sixteen channels, the **LineSelect®** Model 9050 RJ11/12 A/B switch allows the user to access two RJ11/12 interface devices connected to its A and B ports with one RJ11/12 device connected to its COMMON port. The unit supports 4 center pins of the RJ11/12 interface. The sixteen channels are switched simultaneously via one knob located on the front panel. No need to plug and unplug cables thereby eliminating connector wear. The **LineSelect®** Model 9050 is enclosed in a 2U, full rack size, all metal black chassis designed to provide EMI/RFI shielding and fit in a standard 19" rack.

FEATURES:

- Each channel allows quick connection to any one of two devices from one COMMON device.
- Simultaneously switch all sixteen channels between Positions A and B via the front panel rotary switch.
- **High quality sealed switch with self-wiping low impedance contacts.**
- The switch ports are transparent to all data.
- Four center pins 2, 3, 4, 5 of the RJ11/12 interface are switched via a break-before-make rotary switch.
- Eliminates the need to plug and unplug cables.
- Manually operated. No power required.
- Attractive all metal black box packaging provides EMI/RFI shielding.
- Custom length, high quality RJ11/12 patchcords available for your installation.
- **Lifetime warranty against manufacturing defects.**



SPECIFICATIONS:

PORT CONNECTORS: (48) RJ11/12 female connectors; (16) A, (16) B and (16) COMMON.

FRONT PANEL CONTROL: (1) Rotary switch on front panel selects A or B.

POWER: No power required. Manually Operated.

DIMENSIONS: Rackmount: 19.0" W x 3.5" H x 8.6" D. (48.3 x 8.9 x 22.0 cm).

WEIGHT: Approximately 5.7 lb. (2.6 kg)

LineSelect® Model 9050 16-Channel RJ11/12 A/B Application

