



LineSelect® Model 8511 Dual-Channel 8-Port BNC Switch, Manual Desktop

- **Quickly and easily, share a single Dual Channel BNC interface device among 8 other devices.**
- **Field proven in Integration and Test applications.**

INTRODUCTION

The **LineSelect®** Model 8511 Dual-Channel 8-Port BNC Switch allows the user to switch one pair of BNC ports (COMMON, A and B) to the selected pair of BNC ports (A and B) of Channels 1 thru 8.

The **LineSelect®** Model 8511 is packaged in a slim desktop style enclosure.

FEATURES

- **Reliable 8-port BNC switch.**
- **Eliminates the need to plug and unplug cables.**
- **One pole of each port is switched (center pin).**
- **The shell of all BNC's are connected together at all times (not isolated)**
- **The switch ports are transparent to all data.**
- **Manual operation via front panel mechanical pushbutton switch.**
- **Simultaneous control of both channels.**
- **No external power required.**
- **Attractive all metal black box packaging provides EMI/RFI shielding.**
- **Lifetime warranty against manufacturing defects.**
- **Custom length BNC Coaxial cables available for your switch installation.**



SPECIFICATIONS:

PORT CONNECTORS: (18) Coaxial female connectors labeled 1A & 1B, 2A & 2B, thru 8A & 8B and COMMON A & B.

FRONT PANEL CONTROLS: (8) Manual pushbuttons allows local switching.

POWER: No power required.

DIMENSIONS: 8.5" W x 1.7 H x 7.6" D.
(21.6 x 4.3 x 19.3 cm)

WEIGHT: Approximately 1.5 lbs. (0.7 kg)

Suggested cables for use with Model 8022 Switch. Specify the length (XXX) when ordering.

Part Number	Description	Price (USD)
990136-XXX	XXX Feet, M/M, 50 ohm, BNC Coaxial Cable, PVC	\$30.00 + 0.35 / FT
990137-XXX	XXX Feet, M/M, 75 ohm, BNC Coaxial Cable, PVC	\$30.00 + 0.35 / FT
990138-XXX	XXX Feet, M/M, 93 ohm, BNC Coaxial Cable, PVC	\$30.00 + 0.40 / FT

