

## LineSelect® Model 9451 DB25 A/B/C Switch, Manual, Rackmount

- Provides reliable network backup for mission critical systems.

### INTRODUCTION

The **LineSelect®** Model 9451 DB25 A/B/C Switch allows the user to access three DB25 devices connected to its A, B, and C ports with one DB25 device connected to its COMMON port. The unit is manually operated, requiring no power. Port selection is quick and easy via a front panel rotary switch. The **LineSelect®** Model 9451 is enclosed in a 1U, full rack size, all metal black chassis designed to provide EMI/RFI shielding and fit in a standard 19" rack.

### FEATURES:

- Allows quick connection to any one of three DB25 devices or networks from one COMMON device or network.
- Manual operation via front-panel rotary switch.
- High quality sealed switch with self-wiping low impedance contacts.
- Transparent to data speed and format.
- All 25 pins of the DB25 interface are switched via break-before-make rotary switch.
- Eliminates the need to plug and unplug cables.
- No external power required.
- Attractive all metal black box packaging provides EMI/RFI shielding.
- Custom length DB25 cables available for your switch installation.
- **Lifetime warranty against manufacturing defects.**



### SPECIFICATIONS:

**PORT CONNECTORS:** (4) DB25 female connectors labeled A, B, C and COMMON.

**FRONT PANEL CONTROL:** (1) Rotary switch on front panel selects A, B, C.

**LIFE:** 10,000 cycles at the rate of 20-25 cycles/minute and no load.

**OPERATING & STORAGE TEMP:** -10° C to +60° C.

**POWER:** No power required. Manually operated.

**DIMENSIONS:** Rackmount 19.0" W x 1.75" H x 8.75" D. (48.3 x 4.5 x 22.3 cm)

**WEIGHT:** Approximately 4.4 lbs. (2.0 kg)

### Ask about our popular

#### Model 700 RS232 Breakout Box

Tri-State LED's monitor the data interface and "TELL ALL" for fault isolation.



### Custom length data network cables 25-conductor, DB25/DB25, Unshielded, PVC.

| Part Number | Connectors | Length Specify XXX-FT | Price (USD)         |
|-------------|------------|-----------------------|---------------------|
| 990104-XXX  | F/F        | XXX-FT                | \$24.00 + 0.55 / FT |
| 990105-XXX  | M/F        | XXX-FT                | \$24.00 + 0.55 / FT |
| 990106-XXX  | M/M        | XXX-FT                | \$24.00 + 0.55 / FT |

### LineSelect® Model 9451 A/B/C Switch Application

